

**LS16 2150A AC**  
**LS162150A1FPA000**  
16-Way Active Splitter (950-2150 MHz)

**General Description:**

The **LS162150A1FPA000** is a commercial quality 16-way splitter that meets strict level and match specifications achieved through the use of Quintech's proprietary microstrip and SMT technology. It operates over the 950-2150 MHz frequency range and permits signal splitting with zero loss, eliminating the need for external distribution amplifiers. The LS162150A1FPA000 provides LNB DC power insertion that can be switched on or off via the front panel mounted slide switch (see LNB Power specification below).

Note: All unused RF output ports must have 75  $\Omega$  terminations.

**Specifications:**

<b>Frequency:</b>	950-2150 MHz
<b>Impedance:</b>	75 $\Omega$
<b>P1dB:</b>	0 dBm
<b>OIP<sup>3</sup>:</b>	+10 dBm
<b>Insertion Loss:</b>	0 $\pm$ 2 dB
<b>Frequency Response:</b>	$\pm$ 2 dB
<b>Isolation:</b>	18 dB
<b>Input Return Loss:</b>	14 dB
<b>Output Return Loss:</b>	12 dB
<b>Noise Figure:</b>	8 dB
<b>RF Connectors:</b>	Type F, 75 $\Omega$
<b>Power Requirements:</b>	100-240 V~, 50/60 Hz
<b>LNB Power:</b>	24 V $\overline{=}$ , 800 mA max. available per LNB power
<b>Power Consumption:</b>	10 W, plus customer LNB power load
<b>Mechanical:</b>	1 RU (1.75" H x 19" W x 6.5" D)
<b>Weight:</b>	5.0 lbs. gross (boxed), 3.0 lbs. net
<b>Certifications:</b>	CE



250 Airport Road • Indiana, PA 15701 • (800) 839-3658 • (724) 349-1412 • Fax: (724) 349-1421

<http://www.quintechelectronics.com/> • [info@quintechelectronics.com](mailto:info@quintechelectronics.com)